

## HALLICRAFTERS SX-140 RECEIVER



Amateur Band Communications Receiver

Made In: United States 1965-1968 Voltages: 105-125 VAC 50/60 Hz

Coverage: Ham. See Comments Readout: Analog Lin.

Modes: AM/CW-LSB/USB Selectivity: 2.1/\_/\_ kHz

Circuit: Single Conversion Superheterodyne. 9 Tubes plus Semiconductors.

Circuit Complement: 6JD6 RF Amp, 6GW8 Audio Amp & Output, 12AT7 Mixer, 6BA6 VFO, 6AU6A IF Amp, 6AU6 IF Amp, 6EA8 Osc. & Premix, 12AT7 AM Detector/AVC Rectifier, 12AT7 USB/LSB Crystal Osc. and 6AU6A Calibrator.

Features: • ¼" Head. Jack • S-Meter • AVC ON/OFF • Preselector • RF Gain • ANL • Mute Line • Extl. Osc. Input • BFO • Fiduciary Adjust • Flywheel Tuning • Speaker Terminals

Accessories: 49-321 .5 kHz Filter, 49-319 5 kHz Filter, HA-19 Calibrator 100 kHz, R-50 Speaker, R-51 Speaker/Clock

New Price: \$250-295 Used Price: \$160-200

Comments: Ranges: 3.5-4, 7-7.5, 14-14.5, 21-21.5, 28-28.5, 29-29.5<sup>1</sup> and 29.5-30<sup>1</sup> MHz. <sup>1</sup>This range requires an optional crystal. Matches the HT-46 transmitter. Requires a speaker.