

## HALLICRAFTERS SX 130 RECEIVER



General Coverage Communications Receiver

Made In: United States 1965-1969 Voltages: 105-125 VAC 50/60 Hz

Coverage: 535 - 31500 kHz<sup>1</sup> Readout: Analog

Modes: AM/SSB-CW Selectivity: Wide/Normal/Narrow

Circuit: Single Conversion Superheterodyne. 7 Tubes plus Semiconductors.

Circuit Complement: 6DC6 RF Amp, 6EA8 Mixer/Osc, 6EA8 1st IF Amp/Crystal Sel., 6BA6 2nd IF Amp, 6AL5 AM Detector/NL, 6BE6 BFO/Product Detector, 6GW8 AF Amp/Output and diode.

Features: • $\frac{1}{4}$ " Head. Jack • S-Meter • Bandspread • Product Det. SSB/CW • RF Gain • ANL • BFO • Antenna Trimmer • Mute Terminals • Crystal Phasing • Dial Lamp • Speaker Terminals

Accessories: HA-7 Calibrator, R-47 Speaker, R-50 Speaker, R-51 Speaker/Clock

New Price: \$170-200 Used Price: \$90-140

Comments: Ranges: .535-1.61, 1.725-4.7, 4.5-13 and 11.9-31.5 MHz. <sup>1</sup>Reception gap from 1610-1725 kHz. Bandspread ranges: 3.5-4, 7-7.4, 13.9-14.4, 20-22 and 26-30 MHz. Note that the bandspread occupies the long horizontal dial and the main tuning occupies the smaller rotary dial.

Variants: The model S-129, previously shown, is the same as the SX-130 less crystal filter, crystal phasing and S-Meter \$165.