

HALLICRAFTERS SX-133 RECEIVER



General Coverage Communications Receiver

Made In: United States 1968-1972 Voltages: 117 VAC 50/60 Hz

Coverage: 535 - 31500 kHz¹ Readout: Analog

Modes: AM/LSB/USB-CW Selectivity: 5/2.5/.5 kHz

Circuit: Single Conversion Superheterodyne. 7 Tubes.

Circuit Complement: 6DC6 RF Amp, 6EA8 Mixer/Osc, 6EA8 1st IF Amp/Crystal Sel., 6BA6 2nd IF Amp, 6AL5 AM Detector/NL, 6BE6 BFO/Product Detector, 6GW8 AF Amp/Output and diode.

Features: • ¼" Head. Jack • S-Meter • Bandsread • Product Det. SSB/CW • RF Gain • ANL • BFO • Antenna Trimmer • Mute Terminals • Crystal Phasing • Dial Lamp • Speaker Terminals

Accessories: R-47 Speaker, R-50 Speaker, HA-19 Calibrator 100 kHz, R-51 Speaker/Clock

New Price: \$250-350 Used Price: \$110-250

Comments: Main ranges: .535-1.61, 1.725-4.7, 4.5-13 and 11.9-31.5 MHz. ¹ Reception gap from 1610-1725 kHz. Bandsread ranges: 3.5-4, 6.9-7.4, 13.5-14.4, 20-22, 26-30, 5.9-6.25, 9.45-9.8, 11.65-12 and 15.05-15.5 MHz. Note that the bandsread occupies the long horizontal dial and the main tuning occupies the smaller rotary dial. The bandsread of the 49, 31, 25 and 19 meter bands makes this radio more attractive to the shortwave listener than the SX-130.