

HALLICRAFTERS SX-146 RECEIVER



Amateur Band Communications Receiver (4) Made In: United States 1965-1968 **Voltages:** 105-125 VAC 50/60 Hz **Coverage:** Ham. See Comments **Readout:** Analog Lin. **Modes:** AM/CW-LSB/USB **Selectivity:** 2.1/_/_ kHz **Circuit:** Single Conversion Superheterodyne. 9 Tubes plus Semiconductors. **Physical:** **Circuit Complement:** 6JD6 RF Amp, 6GW8 Audio Amp & Output, 12AT7 Mixer, 6BA6 VFO, 6AU6A IF Amp, 6AU6 IF Amp, 6EA8 Osc. & Premix, 12AT7 AM Detector/AVC Rectifier, 12AT7 USB/LSB Crystal Osc. and 6AU6A Calibrator. **Features:** • ¼" Head. Jack • S-Meter • AVC ON/OFF • Preselector • RF Gain • ANL • Mute Line • Extl. Osc. Input • BFO • Fiduciary Adjust • Flywheel Tuning • Speaker Terminals **Accessories:** 49-321 .5 kHz Filter, 49-319 5 kHz Filter, HA-19 Calibrator 100 kHz, R-50 Speaker, R-51 Speaker/Clock **New Price:** \$250-295 **Used Price:** \$160-200 **Comments:** Ranges: 3.5-4, 7-7.5, 14-14.5, 21-21.5, 28-28.5, 29-29.5¹ and 29.5-30¹ MHz. ¹This range requires an optional crystal. Matches the HT-46 transmitter. Requires a speaker.

1.