

|                                                              |                                                                                                                                                                                                                                                                                                     |
|--------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Rear Apron Connections. ....                                 | Spare socket.<br>HF Antenna.<br>VHF #1 Antenna.<br>VHF #2 Antenna.<br>Mute.<br>Spare socket.<br>ANTI-VOX 500 $\Omega$ .<br>8 $\Omega$ speaker.<br>Line cord socket.<br>Heterodyne Oscillator Output.<br>LMO output.<br>BFO output.<br>VHF Converter socket.                                         |
| Tube Complement. ....                                        | 1 - 6BZ6 RF amplifier.<br>1 - 6AU6 1st mixer.<br>1 - 6AB4 Heterodyne oscillator.<br>1 - 6AU6 2nd mixer.<br>1 - 6AU6 Linear master oscillator.<br>2 - 6BA6 IF amplifier.<br>1 - 6AU6 Crystal calibrator.<br>1 - 6HF8 1st audio, audio output.<br>1 - 6AS11 Product detector, BFO, and BFO amplifier. |
| Power Supply. ....                                           | Transformer operated with silicon diode rectifiers.                                                                                                                                                                                                                                                 |
| Power Requirements. ....                                     | 120 volts AC, 50/60 cps, 50 watts.                                                                                                                                                                                                                                                                  |
| Dimensions. ....                                             | 14-7/8" wide x 6-5/8" high x 13-3/8" deep.                                                                                                                                                                                                                                                          |
| Net Weight. ....                                             | 17 lbs.                                                                                                                                                                                                                                                                                             |
| Shipping Weight. ....                                        | 22 lbs.                                                                                                                                                                                                                                                                                             |
| <hr/>                                                        |                                                                                                                                                                                                                                                                                                     |
| Test Equipment Used To Make Specification Measurements. .... | Hewlett-Packard Signal Generator, Model 606A.<br>Radio Products, Inc. Panoramic Analyzer, Model SB-12<br>Hewlett-Packard Electronic Counter, Model 524B.<br>Boonton Electronics Distortion Analyzer, Model 330B.<br>Daven Company Power Output Meter, Type OP961.                                   |