

SECTION 6. PARTS LIST (CONT'D)

6.2 Radio Receiver

SYMBOL NUMBER	FUNCTION	DESCRIPTION	MFR.	MFR. TYPE NO.
CAPACITORS				
C-101	V-109 Cathode By-pass	Paper: .25 mfd. 200 V DC W	11	0252AA
C-102	V-106A to V-109 Coupling	Paper: .1 mfd. 600 V DC W	11	G016AB
C-103	V-106A Cathode By-pass	Elect: 25 mfd. 50 V DC W	3	FA10062
C-104	Tone Control	Mica: .001 mfd. 500 V DC W	1	1467
C-105	Main Tuning	Variable Air: 3 gang, 12 to 225 mmf. per section	8	NPW3-225
C-106	V-107B Output By-Pass	Mica: .00025 mfd. 500 V DC W	1	1468
C-107	Tone Control	Paper: .01 mfd. 600 V DC W	11	G116AB
C-108	V-107A to V-107B Coupling	Paper: 1 mfd. 200 V DC W	1	284
C-109	V-107A Cathode By-pass	Same as C-106		
C-110	V-106A Plate By-pass	Same as C-106		
C-111	V-105 B+ By-pass	Same as C-102		
C-112	V-105 Screen By-pass	Paper: .1 mfd. 400 V DC W	11	014AB
C-113	V-105 Cathode By-pass	Same as C-112		
C-114	V-105 Grid Filter	Same as C-107		
C-115	V-104 B+ By-pass	Same as C-102		
C-116	V-104 Cathode By-pass	Same as C-112		
C-117	V-104 Grid Filter	Same as C-107		
C-118	V-102 and V-103 B+ By-pass	Same as C-102		
C-119	V-102 Cathode By-pass	Same as C-112		
C-120	V-101 and V-104 B+ By-pass	Same as C-102		
C-121	V-101 Screen By-pass	Same as C-112		
C-122	V-101 Cathode By-pass	Same as C-112		
C-123	V-101 Grid Filter	Mica: .005 mfd. 300 V DC W	1	1467
C-124	V-101 Grid Filter	Same as C-107		
C-125	V-103 Grid	Mica: .0001 mfd. 500 V DC W	1	1468
C-126	V-103 Heater By-pass	Same as C-107		
C-127	V-103 Screen By-pass	Same as C-112		
C-128	V-103 to V-102 Coupling	Same as C-107		
C-129	CW Osc. Vernier	Variable Air: 3 to 10 mmf.	8	CWV-100
C-130	V-108 Grid	Mica: .001 mfd. 500 V DC W	1	1460