

SYMBOL NUMBER	FUNCTION	DESCRIPTION	MFR.	MFR. TYPE NO.
CAPACITORS (CONT'D)				
C-131	V-108 Heater By-pass	Same as C-112		
C-132	V-108 Screen By-pass	Same as C-112		
C-133	V-106B Cathode By-pass	Same as C-112		
C-134	Power Supply Filter	Oil: 4 mfd. 600 V DC W	3	TLAD-6040
C-135	Power Supply Filter	Same as C-134		
C-136	Power Supply Filter	Same as C-134		
C-137	Power Supply Filter	Same as C-134		
C-138	V-107B to V-106A Coupling	Same as C-107		
C-139	V-106B Plate By-pass	Same as C-112		
C-140	V-108 to V-107A Coupling	Bakelite: 1 mmf. 400 V DC W	8	B22
C-141	V-107A to V-106B Coupling	Mica: .00005 mfd. 500 V DC W	1	1468
C-142	H.F.Osc. pad., 200 to 400 kcs.	Mica: .000175 mfd. 500 V DC W	1	1467
C-143	H.F.Osc. pad., 1.3 to 2.8 mcs.	Mica: .0008 mfd. 500 V DC W	1	1467
C-144	H.F.Osc. pad., 2.8 to 6.4 mcs.	Mica: .00136 mfd. 500 V DC W	1	1467
C-145	H.F.Osc. pad., 6.4 to 14. mcs.	Mica: .0031 mfd. 300 V DC W	1	1467
C-146	H.F.Osc. pad., 14. to 30. mcs.	Mica: .00098 mfd. 500 V DC W	1	1467
C-147	H.F.Osc. pad., 200 to 400 kcs.	Variable Air: 3 to 30 mmf.	8	M30
C-148	Not Used			
C-149	T-121 Pri. Tuning	Variable Air: 6 to 85 mmf.	8	
C-150	T-121 Sec. Tuning	Same as C-149		
C-151	T-103 Pri. Tuning	Same as C-149		
C-152	T-103 Sec. Tuning	Same as C-149		
C-153	T-102 Pri. Tuning	Same as C-149		
C-154	T-102 Sec. Tuning	Same as C-149		
C-155	Not Used			
C-156	Not Used			
C-157	T-104 Tuning	Same as C-151		
C-158	V-109 Plate By-pass	Mica: .0085 mfd. 300 V DC W	1	1467
C-159	V-107A Plate By-pass	Paper: .05 mfd. 600 V DC W	11	GL56AB
C-160	R.F.Amp.Pad., 14 to 30 mcs.	Same as C-146		
C-161	H.F.Osc.Trim. 200 to 400 kcs.	Variable Air: 8 to 75 mmf.	8	
C-162	H.F.Osc.Trim. 1.3 to 2.8 mcs.	Variable Air: 4 to 23 mmf.	8	
C-163	H.F.Osc.Trim. 2.8 to 6.4 mcs.	Variable Air: 3.5 to 19 mmf.	8	
C-164	H.F.Osc.Trim, 6.4 to 14. mcs.	Same as C-163		