

SYMBOL NUMBER	FUNCTION	DESCRIPTION	MFR.	MFR. TYPE NO.
CAPACITORS (CONT'D)				
C-165	H.F.Osc.Trim, 14. to 30. mcs.	Variable Air: 3 to 11 mmf.	8	
C-166	1st Det.Trim, 200 to 400 kcs.	Variable Air: 6 to 45 mmf.	8	
C-167	1st Det.Trim, 1.3 to 2.8 mcs.	Same as C-163		
C-168	1st Det.Trim, 2.8 to 6.4 mcs.	Same as C-163		
C-169	1st Det.Trim, 6.4 to 14. mcs.	Same as C-165		
C-170	1st Det.Trim, 14. to 30. mcs.	Same as C-163		
C-171	R.F.Amp.Trim, 200 to 400 kcs.	Variable Air: 5 to 35 mmf.	8	
C-172	R.F.Amp.Trim, 1.3 to 2.8 mcs.	Same as C-163		
C-173	R.F.Amp.Trim, 2.8 to 6.4 mcs.	Same as C-162		
C-174	R.F.Amp.Trim, 6.4 to 14. mcs.	Same as C-162		
C-175	R.F.Amp.Trim, 14. to 30. mcs.	Same as C-162		
MISCELLANEOUS ELECTRICAL PARTS				
E-101	Antenna Input Terminals	Insulated Binding Posts	8	FWK
E-102	Loud Speaker Output	Insulated Tip Jacks	14	1720
E-103	S-101B Terminals	Insulated Screw Terminals	14	1720
E-104	W-201 Shield Ground	Screw Terminal	8	HC-LUG
E-105	S-101 Knob	Bakelite Knob with Pointer	8	HRP-P
E-106	S-102 Knob	Same as E-105		
E-107	R-144 Knob	Same as E-105		
E-108	R-115 Knob	Same as E-105		
E-109	Not used			
E-110	Not used			
E-111	C-129 Knob	Same as E-105		
E-112	R-116 Knob	Same as E-105		
E-113	Band Changing Knob	Bakelite Knob, 1/4" Shaft	8	HRK
E-114	Main Tuning Knob	Bakelite Knob, 3/16" Shaft	8	HRK
E-115	V-104 Grid Shield	Metal Tube Cap	14	6011
FUSES				
F-101	AC Line Fuse	1 Amp. Glass Enclosed	6	3AG
INDICATING DEVICES				
I-101	"S" Meter Lamp	6.3 V, .25 A Screw Base	4	46