

SYMBOL NUMBER	FUNCTION	DESCRIPTION	MFR.	MFR. TYPE NO.
INDICATING DEVICES (Cont'd)				
I-102	Main Dial Lamp	Same as I-101		
I-103	Main Dial Lamp	Same as I-101		
JACKS				
J-101	Headphone Output	Multi-Circuit Jack	10	705
J-102	Coil Catacomb Grounding	Prong Clip	16	247
INDUCTORS				
L-101	B+ Filter	5000 Turns #31 D.C. Resistance 300 Ohms	8	80
L-102	B+ Filter	Same as L-101		
METERS				
M-101	Signal Strength Meter	0 to 1 Milliammeter	13	RMB-52
DIALS				
N-101	Not used			
N-102	Not used			
N-103	Main Calibration	Etched Scale	8	MDS-100BR
N-104	Auxiliary Logging	Etched Dial	8	VDS-100
MECHANICAL PARTS				
O-101	Pinion Gear	12 Tooth Gear	8	CBP-100
O-102	Gear Rack	9" Gear Rack	8	CBR-100
O-103	Catacomb Rod	7/16" Diam., 16-7/8" Length	8	ROD-100
PLUGS				
P-101	AC Connector	2 prong, 660 W, 250 V	15	150
P-102	Primary Tap Connector	1/4" diam., Brass	8	TP-100
P-103	Coil Catacomb	1/4" diam., Brass	8	CCP-100
RESISTORS				
R-101	V-101 Grid Filter	500,000 ohm $\frac{1}{2}$ Watt	2	310
R-102	V-101 Cathode Bias	500 ohm $\frac{1}{8}$ Watt	2	310
R-103	V-102 Cathode Bias	5,000 ohm $\frac{1}{2}$ Watt	2	310