

SEQUENCE 12.2.1.1.12  
Restore\_PrimaryN (xPrimary, yPrimary,  
TYPrimary)

8 SEND TO DEVICE TYPE  
BROADCAST  
QUERY COLOUR TYPE FEATURES

Check if device is colour  
temperature Tc capable

(answer and 0x1C) > 0?

No

Yes

nrPrim := ((answer and 0x1C)>>2)  
i := 0

SEND  
BROADCAST  
DTR2 (i)

EXECUTE SEQUENCE  
SetSpecific16bitValue(xPrimary [ i ])

8 SEND TO DEVICE TYPE  
BROADCAST  
SET TEMPORARY x-COORDINATE

Restore temp. x-coordinate

EXECUTE SEQUENCE  
SetSpecific16bitValue(yPrimary [ i ])

8 SEND TO DEVICE TYPE  
BROADCAST  
SET TEMPORARY y-COORDINATE

Rest. temp. y-coordinate

8 SEND TO DEVICE TYPE  
BROADCAST  
STORE xy-COORDINATE PRIMARY N

Rest. xy-coordinate Primary N

EXECUTE SEQUENCE  
SetSpecific16bitValue(TYPrimary [ i ])

8 SEND TO DEVICE TYPE  
BROADCAST  
STORE TY PRIMARY N

Restore TY Primary N

i := i + 1

i = nrPrim ?

No

Yes

Return