

SYMBOL NUMBER	FUNCTION	DESCRIPTION	MFR.	MFR. TYPE NO.
RESISTORS (CONT'D)				
R-104	B+ Voltage Divider	20,000 ohm, 2 Watt	2	316
R-105	V-104 Grid Filter	Same as R-101		
R-106	V-104 Cathode Bias	300 to 5,000 Ohm, $\frac{1}{2}$ Watt	2	310
R-107	V-105 Grid Filter	Same as R-101		
R-108	V-105 Cathode Bias	300 to 5,000 Ohm, $\frac{1}{2}$ Watt	2	310
R-109	V-105 Screen	70,000 Ohm, $\frac{1}{2}$ Watt	2	310
R-110	V-105 Screen Bleeder	100,000 Ohm $\frac{1}{2}$ Watt	2	310
R-111	V-104 Plate Filter	2,000 Ohm $\frac{1}{2}$ Watt	2	310
R-112	V-107A I.F. Filter	Same as R-103		
R-113	V-107A Load	50,000 Ohm, $\frac{1}{2}$ Watt	2	310
R-114	V-107B Input	Same as R-110		
R-115	Tone Control	500,000 Ohm 1 Watt Comp. Var.	2	62-106
R-116	Audio Gain Control	500,000 Ohm 1 Watt Comp. Var.	2	72-105
R-117	V-106A Cathode Bias	Same as R-111		
R-118	V-109 Cathode Bias	250 Ohm, 2 Watt	2	316
R-119	Audio Voltage Divider	450 Ohm, 5 Watt	11	5K
R-120	Audio Voltage Divider	50 Ohm, $\frac{1}{2}$ Watt	2	310
R-121	R.F.Gain Control	10,000 Ohm, 1.5 Watt, W.W.Variable	7	P58-10,000V
R-122	R.F.Gain Control Bleeder	Same as R-113		
R-123	V-101 Grid Filter	Same as R-101		
R-124	B+ Voltage Divider	Same as R-104		
R-125	V-103 Grid Leak	20,000 Ohm, $\frac{1}{2}$ Watt	2	310
R-126	V-103 and V-102 Plate Filter	Same as R-111		
R-127	V-102 Screen	Same as R-110		
R-128	V-103 Screen Bleeder	Same as R-110		
R-129	V-103 Screen	50,000 Ohm, 1 Watt	2	314
R-130	V-108 Plate	250,000 Ohm, $\frac{1}{2}$ Watt	2	310
R-131	V-108 Grid Leak	Same as R-113		
R-132	V-108 Screen Bleeder	Same as R-110		
R-133	AVC Filter	Same as R-101		
R-134	"S" Meter Bridge	1,000 Ohm, $\frac{1}{2}$ Watt	2	310
R-135	"S" Meter Adjustment	1,000 Ohm, W.W. Variable	7	MH-1000
R-136	V-106B Plate	Same as R-101		