

ITEM	CIRCUIT FUNCTION	DESCRIPTION	COLLINS PART NUMBER
C-233	Antenna coupling, band 1	CAPACITOR: ceramic, 100 mmf $\pm 5\%$, 500 WV	916-4059-00
C-234	Antenna coupling, band 2	CAPACITOR: ceramic, 51 mmf $\pm 5\%$, 500 WV	916-0476-00
C-235	Antenna coupling, band 3	CAPACITOR: ceramic, 36 mmf $\pm 5\%$, 500 WV	916-4347-00
C-236	Antenna coupling, bands 4-7	CAPACITOR: ceramic, 22 mmf $\pm 5\%$, 500 WV	916-4323-00
C-237	Antenna coupling, bands 8-15	CAPACITOR: ceramic, 10 mmf ± 1 mmf, 500 WV	916-0139-00
C-238	Antenna coupling, bands 16-30	CAPACITOR: ceramic, 5 mmf $\pm 1/2$ mmf, 500 WV	916-0118-00
C-239	Oscillator plate filter	CAPACITOR: 8 mf, 350 WV	184-6515-00
C-240	V108 Cathode	CAPACITOR: fixed ceramic; 10,000 mmf; 500 WV	913-1188-00
C-301	Mech. filter input tuning	CAPACITOR: mica, 200 mmf $\pm 2\%$; 500 WV	912-0514-00
C-302	Mech. filter output tuning	CAPACITOR: mica, 200 mmf $\pm 2\%$; 500 WV	912-0514-00
C-303	V-301 cathode bypass	CAPACITOR: ceramic, 10,000 mmf; 500 WV	913-1188-00
C-304	V-301 screen bypass	CAPACITOR: ceramic, 10,000 mmf; 500 WV	913-1188-00
C-305	V-301 plate bypass	CAPACITOR: ceramic, 10,000 mmf; 500 WV	913-1188-00
C-306	L-301 tuning	CAPACITOR: mica, 270 mmf $\pm 5\%$; 500 WV	912-0524-00
C-307	V-108 grid coupling	CAPACITOR: mica, 100 mmf $\pm 2\%$; 500 WV	912-0493-00
C-308	V-301 screen bypass	CAPACITOR: ceramic, 10,000 mmf, 500 WV	913-1188-00
C-309	V-301 plate bypass	CAPACITOR: ceramic, 10,000 mmf, 500 WV	913-1188-00
C-310	V-108 grid decoupling	CAPACITOR: ceramic, 10,000 mmf, 500 WV	913-1188-00
C-311	Filter tuning	CAPACITOR: mica, 5 mmf $\pm 5\%$; 500 WV	912-0429-00
C-312	Filter tuning	CAPACITOR: ceramic, 8 mmf $\pm 5\%$; 500 WV	916-0129-00
C-313	Filter tuning	CAPACITOR: mica, 12 mmf $\pm 5\%$; 500 WV	912-0434-00
C-314	Filter tuning	CAPACITOR: mica, 12 mmf $\pm 5\%$; 500 WV	912-0434-00
C-315	Filter tuning	CAPACITOR: mica, 15 mmf $\pm 5\%$; 500 WV	912-0437-00
C-316	Filter tuning	CAPACITOR: mica, 18 mmf $\pm 5\%$; 500 WV	912-0440-00
CR-101	M-101 rectifier	RECTIFIER: dry disk, instrument type	353-3000-00
E-101	K-101 term. bd.	BOARD, terminal	306-0158-00
E-102	Audio output term. bd.	BOARD, terminal	306-0158-00
F-101	Primary power fuse	FUSE: cartridge, 1.5 amp, one time	264-0007-00
I-101	Dial light	LAMP: pilot light, miniature bayonet base bulb, T-3-1/4 bulb	262-3240-00