

# TECHNICAL SPECIFICATION

**Piezoelectric and dielectric devices for frequency control and selection –  
Glossary –  
Part 4-3: Materials – Materials for dielectric devices**



## THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2008 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office  
3, rue de Varembe  
CH-1211 Geneva 20  
Switzerland  
Email: [inmail@iec.ch](mailto:inmail@iec.ch)  
Web: [www.iec.ch](http://www.iec.ch)

### About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

### About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

- Catalogue of IEC publications: [www.iec.ch/searchpub](http://www.iec.ch/searchpub)

The IEC on-line Catalogue enables you to search by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, withdrawn and replaced publications.

- IEC Just Published: [www.iec.ch/online\\_news/justpub](http://www.iec.ch/online_news/justpub)

Stay up to date on all new IEC publications. Just Published details twice a month all new publications released. Available on-line and also by email.

- Electropedia: [www.electropedia.org](http://www.electropedia.org)

The world's leading online dictionary of electronic and electrical terms containing more than 20 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary online.

- Customer Service Centre: [www.iec.ch/webstore/custserv](http://www.iec.ch/webstore/custserv)

If you wish to give us your feedback on this publication or need further assistance, please visit the Customer Service Centre FAQ or contact us:

Email: [csc@iec.ch](mailto:csc@iec.ch)  
Tel.: +41 22 919 02 11  
Fax: +41 22 919 03 00



# TECHNICAL SPECIFICATION

---

**Piezoelectric and dielectric devices for frequency control and selection –  
Glossary –  
Part 4-3: Materials – Materials for dielectric devices**

INTERNATIONAL  
ELECTROTECHNICAL  
COMMISSION

PRICE CODE

**F**

# INTERNATIONAL ELECTROTECHNICAL COMMISSION

## PIEZOELECTRIC AND DIELECTRIC DEVICES FOR FREQUENCY CONTROL AND SELECTION – GLOSSARY –

### Part 4-3: Materials – Materials for dielectric devices

#### FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with an IEC Publication.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

The main task of IEC technical committees is to prepare International Standards. In exceptional circumstances, a technical committee may propose the publication of a technical specification when

- the required support cannot be obtained for the publication of an International Standard, despite repeated efforts, or
- the subject is still under technical development or where, for any other reason, there is the future but no immediate possibility of an agreement on an International Standard.

Technical specifications are subject to review within three years of publication to decide whether they can be transformed into International Standards.

IEC 61994-4-3, which is a technical specification, has been prepared by IEC technical committee 49: Piezoelectric and dielectric devices for frequency control and selection.

The text of this technical specification is based on the following documents:

Enquiry draft	Report on voting
49/768/DTS	49/780/RVC

Full information on the voting for the approval of this technical specification can be found in the report on voting indicated in the above table.

A list of all parts of IEC 61994 series, published under the general title *Piezoelectric and dielectric devices for frequency control and selection – Glossary* can be found on the IEC website.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

The committee has decided that the contents of this publication will remain unchanged until the maintenance result date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- transformed into an International standard,
- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

A bilingual version of this publication may be issued at a later date.

# PIEZOELECTRIC AND DIELECTRIC DEVICES FOR FREQUENCY CONTROL AND SELECTION – GLOSSARY –

## Part 4-3: Materials – Materials for dielectric devices

### 1 Scope

This part of IEC 61994 specifies the terms and definitions for materials applied for devices using waveguide type dielectric resonators representing the state-of-the-art, which are intended for use in the standards and documents of IEC TC 49.

### 2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 61338-1: 2004, *Waveguide type dielectric resonators – Part 1: Generic specification*

### 3 Terms and definitions

For the purposes of this document, the terms and definitions of IEC 61338-1 apply, notably the following.

#### 3.1

##### **dielectric material**

material which predominantly exhibit dielectric properties

[IEC 61338-1]

#### 3.2

##### **dielectric resonator material**

dielectric materials defined to be used for resonator application at high frequency, i.e. UHF or SHF range. The dielectric material is required to have high relative permittivity, a low loss factor and a minimal temperature coefficient of permittivity

[IEC 61338-1]

#### 3.3

##### **electric constant**

$\epsilon_0$

constant equal to  $8,8542 \times 10^{-12} \text{ AsV}^{-1}\text{m}^{-1}$ , defined by the permittivity of vacuum

[IEC 61338-1]

#### 3.4

##### **relative permittivity**

$\epsilon_r$

absolute permittivity of a material or medium divided by the electric constant  $\epsilon_0$

NOTE The complex relative permittivity  $\underline{\varepsilon}_r$  is defined as

$$\underline{\varepsilon}_r = \varepsilon' - j\varepsilon'', \quad \varepsilon' = \operatorname{Re}(\underline{\varepsilon}_r), \quad \varepsilon'' = \operatorname{Im}(\underline{\varepsilon}_r)$$

where

$\varepsilon'$  is usually called dielectric constant;

$\varepsilon''$  corresponds to the dielectric loss of the material.

[IEC 61338-1]

### 3.5 absolute permittivity

$\varepsilon$

quantity which when multiplied by the electric field strength  $E$  is equal to the electric flux density  $D$

$$D = \varepsilon E, \quad \varepsilon = \varepsilon_0 \varepsilon_r$$

[IEC 61338-1]

### 3.6 loss angle

$\delta$

phase displacement between the component of the electric flux density and the electric field strength

[IEC 61338-1]

### 3.7 loss factor

tangent of the loss angle  $\delta$

$$\tan \delta = \varepsilon'' / \varepsilon'$$

NOTE The loss factor can be determined by the ratio of the negative part to the real part of the complex relative permittivity.

[IEC 61338-1]

### 3.8 quality factor of a material

$Q_0$

reciprocal of the tangent of the loss angle

$$Q_0 = \varepsilon' / \varepsilon'' = 1 / \tan \delta$$

NOTE The quality factor of a material is also defined as  $2\pi$  times the ratio of the stored electromagnetic energy to the energy dissipated in the material per cycle. It is frequency dependent.

[IEC 61338-1]

### 3.9 temperature coefficient of permittivity

$TC\varepsilon$

fractional change of permittivity due to a change in temperature divided by the change in temperature

$$TC\varepsilon = \frac{\varepsilon_T - \varepsilon_{\text{ref}}}{\varepsilon_{\text{ref}}(T - T_{\text{ref}})} \times 10^6 \quad [1 \times 10^{-6}/\text{K}]$$

where

$\varepsilon_T$  is the permittivity at temperature  $T$ ;

$\varepsilon_{\text{ref}}$  is the permittivity at reference temperature  $T_{\text{ref}}$ .

[IEC 61338-1]

### 3.10

#### coefficient of linear thermal expansion

$\alpha$

fractional change of dimension due to a change in temperature divided by the change in temperature

$$\alpha = \frac{l_T - l_{\text{ref}}}{l_{\text{ref}}(T - T_{\text{ref}})} \times 10^6 \quad [1 \times 10^{-6}/\text{K}]$$

where

$l_T$  is the dimension at temperature  $T$ ;

$l_{\text{ref}}$  is the dimension at reference temperature  $T_{\text{ref}}$ .

[IEC 61338-1]

### 3.11

#### dielectric resonator

resonator using dielectrics with a high dielectric constant and the structure of which is a dielectric waveguide of finite length

NOTE The dielectric resonators in use are always shielded with conductors.

[IEC 61338-1]

### 3.12

#### dielectric support

element supporting a dielectric resonator. The support is generally used for  $TE_{01\delta}$  mode resonators and has a low dielectric constant

[IEC 61338-1]





INTERNATIONAL  
ELECTROTECHNICAL  
COMMISSION

3, rue de Varembé  
P.O. Box 131  
CH-1211 Geneva 20  
Switzerland

Tel: + 41 22 919 02 11  
Fax: + 41 22 919 03 00  
[info@iec.ch](mailto:info@iec.ch)  
[www.iec.ch](http://www.iec.ch)